Using one-X® Mobile Preferred for IP Office™ Platform on Android

Release 10.0
Issue 01.01
August 2016

© 2014-2016, Avaya, Inc.
All Rights Reserved.

Notice

While reasonable efforts have been made to ensure that the information in this document is complete and accurate at the time of printing, Avaya assumes no liability for any errors. Avaya reserves the right to make changes and corrections to the information in this document without the obligation to notify any person or organization of such changes.

Documentation disclaimer

“Documentation” means information published by Avaya in varying mediums which may include product information, operating instructions and performance specifications that Avaya may generally make available to users of its products and Hosted Services. Documentation does not include marketing materials. Avaya shall not be responsible for any modifications, additions, or deletions to the original published version of documentation unless such modifications, additions, or deletions were performed by Avaya. End User agrees to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation, to the extent made by End User.

Link disclaimer

Avaya is not responsible for the contents or reliability of any linked websites referenced within this site or documentation provided by Avaya. Avaya is not responsible for the accuracy of any information, statement or content provided on these sites and does not necessarily endorse the products, services, or information described or offered within them. Avaya does not guarantee that these links will work all the time and has no control over the availability of the linked pages.

Warranty

Avaya provides a limited warranty on Avaya hardware and software. Refer to your sales agreement to establish the terms of the limited warranty. In addition, Avaya’s standard warranty language, as well as information regarding support for this product while under warranty is available to Avaya customers and other parties through the Avaya Support website: https://support.avaya.com/helpcenter/getGenericDetails?detailId=C20091120112456651010 under the link “Warranty & Product Lifecycle” or such successor site as designated by Avaya. Please note that if You acquired the product(s) from an authorized Avaya Channel Partner outside of the United States and Canada, the warranty is provided to You by said Avaya Channel Partner and not by Avaya.

“Hosted Service” means a hosted service subscription that You acquire from either Avaya or an authorized Avaya Channel Partner (as applicable) and which is described further in Hosted SAS or other service description documentation regarding the applicable hosted service. If You purchase a Hosted Service subscription, the foregoing limited warranty may not apply but You may be entitled to support services in connection with the Hosted Service as described further in your service description documents for the applicable Hosted Service. Contact Avaya or Avaya Channel Partner (as applicable) for more information.

Hosted Service

THE FOLLOWING APPLIES IF YOU PURCHASE A HOSTED SERVICE SUBSCRIPTION FROM AVAYA OR AN AVAYA CHANNEL PARTNER (AS APPLICABLE), THE TERMS OF USE FOR HOSTED SERVICES ARE AVAILABLE ON THE AVAYA WEBSITE, HTTPS://SUPPORT.AVAYA.COM/LICENSEINFO UNDER THE LINK “Avaya Terms of Use for Hosted Services” OR SUCH SUCCESSOR SITE AS DESIGNATED BY AVAYA, AND ARE APPLICABLE TO ANYONE WHO ACCESSES OR USES THE HOSTED SERVICE. BY ACCESSING OR USING THE HOSTED SERVICE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE DOING SO (HEREINAFTER REFERRED TO INTERCHANGEABLY AS “YOU” AND “END USER”), AGREE TO THE TERMS OF USE. IF YOU ARE ACCEPTING THE TERMS OF USE ON BEHALF A COMPANY OR OTHER LEGAL ENTITY, YOU REPRESENT THAT YOU HAVE THE AUTHORITY TO BIND SUCH ENTITY TO THESE TERMS OF USE. IF YOU DO NOT HAVE SUCH AUTHORITY, OR IF YOU DO NOT WISH TO ACCEPT THESE TERMS OF USE, YOU MUST NOT ACCESS OR USE THE HOSTED SERVICE OR AUTHORIZE ANYONE TO ACCESS OR USE THE HOSTED SERVICE. YOUR USE OF THE HOSTED SERVICE SHALL BE LIMITED BY THE NUMBER AND TYPE OF LICENSES PURCHASED UNDER YOUR CONTRACT FOR THE HOSTED SERVICE, PROVIDED, HOWEVER, THAT FOR CERTAIN HOSTED SERVICES IF APPLICABLE, YOU MAY HAVE THE OPPORTUNITY TO USE FLEX LICENSES, WHICH WILL BE INVOICED ACCORDING TO ACTUAL USAGE ABOVE THE CONTRACT LICENSE LEVEL. CONTACT AVAYA OR AVAYA’S CHANNEL PARTNER FOR MORE INFORMATION ABOUT THE LICENSES FOR THE APPLICABLE HOSTED SERVICE, THE AVAILABILITY OF ANY FLEX LICENSES (IF APPLICABLE), PRICING AND BILLING INFORMATION, AND OTHER IMPORTANT INFORMATION REGARDING THE HOSTED SERVICE.

Licenses

THE SOFTWARE LICENSE TERMS AVAILABLE ON THE AVAYA WEBSITE, HTTPS://SUPPORT.AVAYA.COM/LICENSEINFO, UNDER THE LINK “AVAYA SOFTWARE LICENSE TERMS (Avaya Products)” OR SUCH SUCCESSOR SITE AS DESIGNATED BY AVAYA, ARE APPLICABLE TO ANYONE WHO DOWNLOADS, USES AND/OR INSTALLS AVAYA SOFTWARE, PURCHASED FROM AVAYA INC., ANY AVAYA AFFILIATE, OR AN AVAYA CHANNEL PARTNER (AS APPLICABLE) UNDER A COMMERCIAL AGREEMENT WITH AVAYA OR AN AVAYA CHANNEL PARTNER. UNLESS OTHERWISE AGREED TO BY AVAYA IN WRITING, AVAYA DOES NOT EXTEND THIS LICENSE IF THE SOFTWARE WAS OBTAINED FROM ANYONE OTHER THAN AVAYA, AN AVAYA AFFILIATE OR AN AVAYA CHANNEL PARTNER; AVAYA RESERVES THE RIGHT TO TAKE LEGAL ACTION AGAINST YOU AND ANYONE ELSE USING OR SELLING THE SOFTWARE WITHOUT A LICENSE. BY INSTALLING, DOWNLOADING OR USING THE SOFTWARE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE INSTALLING, DOWNLOADING OR USING THE SOFTWARE (HEREINAFTER REFERRED TO INTERCHANGEABLY AS “YOU” AND “END USER”), AGREE TO THESE TERMS AND CONDITIONS AND CREATE A BINDING CONTRACT BETWEEN YOU AND AVAYA INC. OR THE APPLICABLE AVAYA AFFILIATE (“AVAYA”).

Avaya grants You a license within the scope of the license types described below, with the exception of Heritage Nortel Software, for which the scope of the license is detailed below. Where the order documentation does not expressly identify a license type, the applicable license will be a Designated System License. The applicable number of licenses and units of capacity for which the license is granted will be one (1), unless a different number of licenses or units of capacity is specified in the documentation or other materials available to You. “Software” means computer programs in object code, provided by Avaya or an Avaya Channel Partner, whether as stand-alone products, pre-installed on hardware products, and any upgrades, updates, patches, bug fixes, or modified versions thereto. “Designated Processor” means a single stand-alone computing device. “Server” means a Designated Processor that hosts a software application to be accessed by multiple users. “Instance” means a single copy of the Software executing at a particular time: (i) on one physical machine; or (ii) on one deployed software virtual machine (“VM”) or similar deployment.

License type(s)

Designated System(s) License (DS). End User may install and use each copy or an Instance of the Software only on a number of Designated Processors up to the number indicated in the order. Avaya may require the Designated Processor(s) to be identified in the order by type, serial number, feature key, Instance, location or other specific designation, or to be provided by End User to Avaya through electronic means established by Avaya specifically for this purpose.

Concurrent User License (CU). End User may install and use the Software on multiple Designated Processors or one or more Servers, so long as only the licensed number of Units are accessing and using the Software at any given time. A “Unit” means the unit on which Avaya, at its sole discretion, bases the pricing of its licenses and can be, without limitation, an agent, port or user, an e-mail or voice mail

account in the name of a person or corporate function (e.g., webmaster or helpdesk), or a directory entry in the administrative database utilized by the Software that permits one user to interface with the Software. Units may be linked to a specific, identified Server or an Instance of the Software.

Database License (DL). End User may install and use each copy or an Instance of the Software on one Server or on multiple Servers provided that each of the Servers on which the Software is installed communicates with no more than one Instance of the same database.

CPU License (CP). End User may install and use each copy or Instance of the Software on a number of Servers up to the number indicated in the order provided that the performance capacity of the Server(s) does not exceed the performance capacity specified for the Software. End User may not re-install or operate the Software on Server(s) with a larger performance capacity without Avaya's prior consent and payment of an upgrade fee.

Named User License (NU). You may: (i) install and use each copy or Instance of the Software on a single Designated Processor or Server per authorized Named User (defined below); or (ii) install and use each copy or Instance of the Software on a Server so long as only authorized Named Users access and use the Software. "Named User", means a user or device that has been expressly authorized by Avaya to access and use the Software. At Avaya's sole discretion, a "Named User" may be, without limitation, designated by name, corporate function (e.g., webmaster or helpdesk), an e-mail or voice mail account in the name of a person or corporate function, or a directory entry in the administrative database utilized by the Software that permits one user to interface with the Software.

Shrinkwrap License (SR). You may install and use the Software in accordance with the terms and conditions of the applicable license agreements, such as "shrinkwrap" or "clickthrough" license accompanying or applicable to the Software ("Shrinkwrap License").

Heritage Nortel Software

"Heritage Nortel Software" means the software that was acquired by Avaya as part of its purchase of the Nortel Enterprise Solutions Business in December 2009. The Heritage Nortel Software is the software contained within the list of Heritage Nortel Products located at https://support.avaya.com/LicenseInfo under the link "Heritage Nortel Products" or such successor site as designated by Avaya. For Heritage Nortel Software, Avaya grants Customer a license to use Heritage Nortel Software provided hereunder solely to the extent of the authorized activation or authorized usage level, solely for the purpose specified in the Documentation, and solely as embedded in, for execution on, or for communication with Avaya equipment. Charges for Heritage Nortel Software may be based on extent of activation or use authorized as specified in an order or invoice.

Copyright

Except where expressly stated otherwise, no use should be made of materials on this site, the Documentation, Software, Hosted Service, or hardware provided by Avaya. All content on this site, the documentation, Hosted Service, and the product provided by Avaya including the selection, arrangement and design of the content is owned either by Avaya or its licensors and is protected by copyright and other intellectual property laws including the sui generis rights relating to the protection of databases. You may not modify, copy, reproduce, republish, upload, post, transmit or distribute in any way any content, in whole or in part, including any code and software unless expressly authorized by Avaya. Unauthorized reproduction, transmission, dissemination, storage, and or use without the express written consent of Avaya can be a criminal, as well as a civil offense under the applicable law.

Virtualization

The following applies if the product is deployed on a virtual machine. Each product has its own ordering code and license types. Note that each Instance of a product must be separately licensed and ordered. For example, if the end user customer or Avaya Channel Partner would like to install two Instances of the same type of products, then two products of that type must be ordered.

Third Party Components

"Third Party Components" mean certain software programs or portions thereof included in the Software or Hosted Service may contain software (including open source software) distributed under third party agreements ("Third Party Components"), which contain terms regarding the rights to use certain portions of the Software ("Third Party Terms"). As required, information regarding distributed Linux OS source code (for those products that have distributed Linux OS source code) and identifying the copyright holders of the Third Party Components and the Third Party Terms that apply is available in the products, Documentation or on Avaya's website at: https://support.avaya.com/Copyright or such successor site as designated by Avaya. The open source software license terms provided as Third Party Terms are consistent with the license rights granted in these Software License Terms, and may contain additional rights benefiting You, such as modification and distribution of the open source software. The Third Party Terms shall take precedence over these Software License Terms, solely with respect to the applicable Third Party Components to the extent that these Software License Terms impose greater restrictions on You than the applicable Third Party Terms.

The following applies if the H.264 (AVC) codec is distributed with the product. THIS PRODUCT IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO (i) ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO") AND/OR (ii) DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION MAY BE OBTAINED FROM MPEG LA, L.L.C. SEE HTTP://WWW.MPEGLA.COM.

Service Provider

THE FOLLOWING APPLIES TO AVAYA CHANNEL PARTNER'S HOSTING OF AVAYA PRODUCTS OR SERVICES. THE PRODUCT OR HOSTED SERVICE MAY USE THIRD PARTY COMPONENTS SUBJECT TO THIRD PARTY TERMS AND REQUIRE A SERVICE PROVIDER TO BE INDEPENDENTLY LICENSED DIRECTLY FROM THE THIRD PARTY SUPPLIER. AN AVAYA CHANNEL PARTNER'S HOSTING OF AVAYA PRODUCTS MUST BE AUTHORIZED IN WRITING BY AVAYA AND IF THOSE HOSTED PRODUCTS USE OR EMBED CERTAIN THIRD PARTY SOFTWARE, INCLUDING BUT NOT LIMITED TO MICROSOFT SOFTWARE OR CODECS, THE AVAYA CHANNEL PARTNER IS REQUIRED TO INDEPENDENTLY OBTAIN ANY APPLICABLE LICENSE AGREEMENTS, AT THE AVAYA CHANNEL PARTNER'S EXPENSE, DIRECTLY FROM THE APPLICABLE THIRD PARTY SUPPLIER.

WITH RESPECT TO CODECS, IF THE AVAYA CHANNEL PARTNER IS HOSTING ANY PRODUCTS THAT USE OR EMBED THE G.729 CODEC, H.264 CODEC, OR H.265 CODEC, THE AVAYA CHANNEL PARTNER ACKNOWLEDGES AND AGREES THE AVAYA CHANNEL PARTNER IS RESPONSIBLE FOR ANY AND ALL RELATED FEES AND/OR ROYALTIES. THE G.729 CODEC IS LICENSED BY SIPRO LAB TELECOM INC. SEE WWW.SIPRO.COM/CONTACT.HTML. THE H.264 (AVC) CODEC IS LICENSED UNDER THE AVC PATENT PORTFOLIO LICENSE FOR THE PERSONAL USE OF A CONSUMER OR OTHER USES IN WHICH IT DOES NOT RECEIVE REMUNERATION TO: (I) ENCODE VIDEO IN COMPLIANCE WITH THE AVC STANDARD ("AVC VIDEO") AND/OR (II) DECODE AVC VIDEO THAT WAS ENCODED BY A CONSUMER ENGAGED IN A PERSONAL ACTIVITY AND/OR WAS OBTAINED FROM A VIDEO PROVIDER LICENSED TO PROVIDE AVC VIDEO. NO LICENSE IS GRANTED OR SHALL BE IMPLIED FOR ANY OTHER USE. ADDITIONAL INFORMATION FOR H.264 (AVC) AND H.265 (HEVC) CODECS MAY BE OBTAINED FROM MPEG LA, L.L.C. SEE HTTP://WWW.MPEGLA.COM.

Compliance with Laws

Customer acknowledges and agrees that it is responsible for complying with any applicable laws and regulations, including, but not limited to laws and regulations related to call recording, data privacy, intellectual property, trade secret, fraud, and music performance rights, in the country or territory where the Avaya product is used.

Preventing Toll Fraud

“Toll Fraud” is the unauthorized use of your telecommunications system by an unauthorized party (for example, a person who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf). Be aware that there can be a risk of Toll Fraud associated with your system and that, if Toll Fraud occurs, it can result in substantial additional charges for your telecommunications services.

Avaya Toll Fraud intervention

If You suspect that You are being victimized by Toll Fraud and You need technical assistance or support, call Technical Service Center Toll Fraud Intervention Hotline at +1-800-643-2353 for the United States and Canada. For additional support telephone numbers, see the Avaya Support website: https://support.avaya.com or such successor site as designated by Avaya.

Security Vulnerabilities

Information about Avaya’s security support policies can be found in the Security Policies and Support section of https://support.avaya.com/security.

Suspected Avaya product security vulnerabilities are handled per the Avaya Product Security Support Flow (https://support.avaya.com/css/P8/documents/100161515).

Downloading Documentation

For the most current versions of Documentation, see the Avaya Support website: https://support.avaya.com, or such successor site as designated by Avaya.

Contact Avaya Support

See the Avaya Support website: https://support.avaya.com for product or Hosted Service notices and articles, or to report a problem with your Avaya product or Hosted Service. For a list of support telephone numbers and contact addresses, go to the Avaya Support website: https://support.avaya.com (or such successor site as designated by Avaya), scroll to the bottom of the page, and select Contact Avaya Support.

Trademarks

The trademarks, logos and service marks (“Marks”) displayed in this site, the Documentation, Hosted Service(s), and product(s) provided by Avaya are the registered or unregistered Marks of Avaya, its affiliates, or other third parties. Users are not permitted to use such Marks without prior written consent from Avaya or such third party which may own the Mark. Nothing contained in this site, the Documentation, Hosted Service(s) and product(s) should be construed as granting, by implication, estoppel, or otherwise, any license or right in and to the Marks without the express written permission of Avaya or the applicable third party.

Avaya is a registered trademark of Avaya Inc.

All non-Avaya trademarks are the property of their respective owners. Linux® is the registered trademark of Linus Torvalds in the U.S. and other countries.

Contents

Chapter 1: About Avaya one-X® Mobile 8
Overview 8
User interface 9
The Home screen 13
Menu Guide screen 14
The Contacts screen 14
The Instant Messages screen 18
The Conference screen 20
The Call Log screen 22
Chapter 2: Getting started 25
Application installation 25
Installing the application on an Android device 25
Configure the application 26
Configuring the connection to IP Office 26
Configure call control 27
Configuring enterprise dialing 29
Configuring the notify me feature 30
Setting preferences for notifications 31
Configuring GPS information 32
Deleting GPS locations 32
Enabling or disabling mobile twinning 33
Configuring DND settings 35
Viewing support information 35
Changing the password 36
Enable the widget 36
Self-administration on Avaya one-X® Portal 37
Chapter 3: Managing Status Information 38
Managing status information 38
Setting your status 40
Using the notify me feature 40
Viewing calendar information 41
Viewing the phone status 41
Chapter 4: Handling Calls 42
Making calls 42
Setting your call facility 42
Initiating a call from the Dialpad 44
Initiating a call from the contacts list 45
Initiating a call from an instant message 45
Initiating a call from the call log 45

Using the integrated dialer ... 45
Initiating an e-mail from the Contacts list ... 46
Making a selection ... 46
Using Avaya one-X® Mobile to call any number on your phone ... 47
Configuring the setting for reading out the name of the caller ... 47
Transferring 3rd-party calls ... 47
Moving a call to other phones ... 48
Handling user call transfers ... 48
Chapter 5: Making conference calls ... 50
Managing your conference bridge ... 50
Adding conference participants ... 51
Starting a conference ... 52
Joining a conference in progress ... 54
Locking and unlocking a conference ... 54
Muting participants ... 54
Disconnecting participants ... 55
Starting an adhoc conference ... 55
Chapter 6: Using the Events history ... 57
About Events history ... 57
Filtering the Events ... 58
Clearing the Events history ... 58
Configuring notification settings for missed calls ... 58
Chapter 7: Managing VoIP calls ... 59
About the VoIP feature ... 59
Prerequisites and supported devices ... 59
Status indicators for VoIP ... 60
Error messages for VoIP ... 61
VoIP interaction with cellular calls ... 61
Making VoIP Calls ... 62
Receiving VoIP Calls ... 62
Interacting with VoIP Calls ... 63
Configuring Codec preferences ... 65
Enabling or disabling notification for VoIP registration ... 65
Configuring bluetooth headset support for VoIP calls ... 66
Recording VoIP calls ... 66
Chapter 8: Using instant messaging ... 67
Sending an instant message ... 67
Receiving instant messages ... 67
Configuring call out for incoming message ... 68
Selecting a view ... 68
Deleting instant messages ... 69
Sending text messages using voice commands ... 69
Initiating a group chat ... 69

Chapter 9: Managing voice mails 71
Managing voicemail 71
Listening to voice mail messages 71
Listening to incoming messages 72
Returning a call 72
Deleting voice mail messages 72
Sending a voice mail message via email 73
Chapter 10: Managing geo-presence information 74
Viewing the geo-presence of a contact 74
Viewing requests for your geo-presence 75
Communications options 75
Chapter 11: Sharing the application feedback 76
Sharing feedback through Facebook 76
Sharing feedback through Twitter 76
Sharing feedback through Mail 77
Sharing feedback through Message 77
Chapter 12: Troubleshooting 79
Uploading logs 79
Submitting a problem 79

Chapter 1: About Avaya one-X® Mobile

Overview

Avaya one-X® Mobile is an application that mobile phone users can use to connect to the IP Officecommunications server. Only IP Office release 8.0+ supports one-X Mobile Preferred.

Designed for a mobile workforce, the Avaya one-X® Mobile application provides rich unified communications (UC) capabilities that help users conduct business while on the move. Avaya one-X® Mobile features include:

- Password change capability from your mobile phone.
- Secure Real-time Transport Protocol (SRTP) support.
- Transport Layer Security (TLS) support with third party certificate validation.
- Automatic Fallback mechanism from Voice Over Internet Protocol (VoIP) to Mobile call-back facility.
- External ringer to ring inspite of a headset jack plugged into the device
- Mechanism to move calls from one call-facility to the other.
- VoIP active call details.
- Search system users and add them to groups.
- Ability to copy paste the number from external application into the dial pad.
- Call recording control option with recordings being visible in Events Tab.
- Track geo-presence for a XMPP group.
- Ability to support voice chat through Siri.
- Support for call out for an incoming call.
- Support for call summary features.

Supported platforms

The one-X Mobile Preferred application is supported on Android mobile phones with OS 2.1 and later. However, VoIP feature is supported on Android 4.x.

User interface

The following sections describe the icons, menus, and controls available on the Avaya one-X® Mobile application.

Layout

The following graphic shows the layout of the Avaya one-X® Mobile interface with the Home screen selected.



No.	Description
1	Connection and event status. If this icon is not visible, ensure that you enable the **Show Notifications** checkbox in your Android device settings under **Settings > Applications > Avaya Mobility App**.
2	Status bar.
3	Navigation bar.
4	Instant Message status. Indicates the total number of Instant Message events.
5	Voicemail status. Indicates the total number of Voicemail events.

Table continues…

No.	Description
6	Conference status. Indicates the total number of Conference events.
7	User avatar. Tap the avatar to access the following options: • **Remove** • **Take picture** • **Pick from gallery** • **Import from Facebook**

The status bar:

The Status bar is available on all screens in the Avaya one-X® Mobile interface. It contains information about your availability, and provides controls for setting your location and enabling or disabling GPS location information. The Status bar also indicates the status of your connection to the server.



	**Status** message. Indicates your current status. Select from a list of defaults, or manually edit the status by tapping on the text element. The default text reads **<set your status here>**.  Select colors to represent your status: • Green: Available • Yellow: Away • Red: Busy or Do Not Disturb
	**Location** icon. Indicates the configuration for your current call facility. Press this icon to edit the configuration.

Table continues…

	For more information, see Setting your location on page 42.
	**Location precision** icon. Indicates your current 'precision' with respect to your geo-presence. The four precision levels are: • City • Neighborhood • Street • Maximum Long-press this icon to access delete options for **All devices** and **This device**.
	**Connection error** icon. If this icon appears on the status bar, you are not connected to the network. Press the **Connection error** icon to view details.

The status bar appears on all screens. However, when you long-press a contact on the Contacts screen, the status bar changes into a *selection* bar. The selection bar lets you easily add users to conferences and contact groups. You can also send the selected contacts a group email or instant message.


The following table explains the items on the selection bar:



	**Conference** icon. Press this button to invite all *selected* contacts to a conference.
	**Options menu** icon. Press this button to view the options available for the *selected* contacts. The options are: • Conference • Send IM • Email • Save to group • Locate

The navigation bar:

The navigation bar allows you to view each of the screens. A red circle over the menu icon on the navigation bar indicates the number of new events, such as new voicemail messages, new instant messages, or new participants in your conference room.



Icons:

The following icons are used on all of the screens to indicate status and event information on the Avaya one-X® Mobile interface and the mobile device.






	**Home screen** icon. Press this button to navigate to the Home screen.
	**Contacts screen** icon. Press this button to navigate to the Contacts screen.
	**Active Calls screen** icon. Press this button to navigate to the Active Calls screen.
	**Instant Message** icon. Press this button to navigate to the Instant Message screen.
	**Conference** icon. Press this button to navigate to the Conference screen.
	**Call Log** icon. Press this button to navigate to the Call Log screen.
	**Notification** icon. This icon appears above the navigation bar buttons to indicate new events for that feature.
The connection icon displays at the top of the screen, and is visible when the Avaya one-X® Mobile application is active on the device. If this icon is not visible, ensure that you enable the **Show Notifications** check box in your Android device settings under **Settings > Applications > Avaya Mobility App**.	
	A green triangle indicates that the application is connected to .

Table continues…

	A red dot in centre of the triangle indicates a new event.
	A yellow triangle indicates that the application is partially connected.
	A red triangle indicates that the application is disconnected.

Menu options and controls

On Android devices, use the following methods to access the menu options in the Avaya one-X® Mobile application:


- **Press**: Press an item to select it.
- **Long-press** (press and hold): Long-pressing a contact name or item provides a menu specific to the selected item.
- **Menu key**: Pressing the **Menu** key on the mobile device will show options for the screen that you are currently viewing. The options apply to the screen, rather than to an individual contact or message on that screen.

The Home screen

Use the Home screen to view a snapshot of your communications.

In the area below the Status bar, the Home screen displays an icon for each type of communication: **Instant Messages**, **Voicemail**, and **Conference Call**. The application updates the icons regularly to display information about new messages or calls.

When you receive a new instant message, the Home screen displays a notification. If you receive more than one message from multiple contacts, the application displays small dots on the icon bar for that message type. These dots allow you to swipe through each message.



Notifications also occur on the Home screen for incoming voicemail messages. You can choose to listen to the message as the application records the message, or you can answer the call.




If you choose to answer the call, the call rings at the location that you have specified as your current location in the Avaya one-X® Mobile application.

If another user dials into your conference bridge, the Home screen displays a button so that you can join the conference with one click.



Menu Guide screen




Android devices such as Samsung Galaxy S5, Micromax Canvas 2, and Asus ZenPhone 6 have three hard buttons. These devices display the Menu Guide screen every time you start the Avaya one-X® Mobile application unless you select the **Don’t show me again** check box.


The Contacts screen

The Contacts screen lists the contacts that you configure using the **People** directory on the Android device, or that your administrator configures on the IP Office call server.

You can create custom local groups by long-pressing a contact from the contact list and then selecting **More > Save to Group**. In the following screenshot, a local group called “Test” has been created:



If you press the **Filter** button next to the **Search** field, you can perform a more advanced selection of contacts by filtering the following groups.



- **Team:** Includes roster contacts, including IP Office colleagues as well as gTalk users added in Avaya one-X® Portal.

  The Team group also has an expanded view to list all XMPP groups containing at least one user. Due to the fact that a given roster contact can belong to multiple groups, the contact counts for the XMPP groups may be greater than the contact count shown for the Team group.

  Note also that the Team group includes a **Hide Offline** option. Enabling this option hides Team contacts that are not offline so that the roster displays only online contacts.
- **Corporate directory:** Includes corporate directory contacts.
- **Personal Directory:** Includes contacts added to your Personal directory. The Personal Directory group appears only if you have added at least one contact to the Personal Directory using Avaya one-X® Portal.
- **My Local Groups:** Includes locally defined groups.
- **My contacts:** Includes personal directory contacts, such as gTalk users.

Note that some users may appear in more than one group (gTalk users, for example).

On the contact list, the color-coded bar to the left of the contact's name indicates the presence status of the contact. If the bar is grey, the contact is offline. If the contact has entered a status message, the message is shown below the contact's name. If the color-coded bar is hollow, it indicates that the contact is external to IP Office and the presence information is not available for that contact.

When you tap a contact, the following options become available for that contact:

- **Call Work**


- **Select**
- **Send IM**
- **Notify Me**
- **Add to conference**
- **Details**

Note:

For contacts with a hollow bar, the Notify Me option is replaced by Email as the presence of these contacts are not available.

Long-pressing the names of contacts lets you select multiple contacts to add to a conference call using the **Options menu** icon. For more information, see Making a selection on page 46. You can also press the **Menu** key on the mobile device and choose either **Select All** or **Refresh Contacts**.

The following image shows the contact details screen that appears when you select **Details**. Depending on the contact's presence information you can choose to have IP Office alert you when the contact's presence changes.



It is also worth noting that the Details screen indicates whether GPS information is available for a contact. If a contact is publishing GPS information, you can view their geo-presence by clicking the **Observer Location** button.

For more information, see Making calls on page 42.

Icons:

	**Dialpad** button. Press the **Dialpad** button to launch the dialpad. For information about making calls using the dialpad, see Using the integrated dialer on page 45.
	**Search** button. Press the **Search** button to enter search mode. This mode includes the auto-complete feature.
	**Filter** button. Press the **Filter** button to perform a more advanced selection of contacts by group. Note that some users may appear in more than one group (gTalk users, for example).

The Instant Messages screen

The Instant Messages screen displays the IMs that you have received.



To view the options for the Instant Messages screen, press the menu key on the mobile phone:

- **Disable History:** By default, the application displays read and unread instant messages. Toggle the display to view new or unread messages.
- **Clear history:** Use this option to delete instant messages that you have read.

When you open an instant message, the application displays information about the sender.

The following table describes the icons that appear at the top of the screen. All options here relate to the user that sent the message:



No.	Description
1	**Observation** Tap to observe the presence of the user.
2	**Outlook Meeting** Tap to view the Outlook Meeting information of the user, if available.
3	**Location information** Tap to view the location information about the user.
4	**Notify Me** Tap to follow the user and determine when the user becomes available.
5	**On the Phone** This icon indicates whether the user is on a phone call.
6	**Add to Conference** Tap to add the user to a conference call.
7	**Call** Tap to call the user.


The Avaya one-X® Mobile application stores up to 1MB of instant messages. The number of instant messages that you can store depends on the number of characters that each message contains. Depending on the length of the message, you can store up to 10,000 messages or even more messages. When you reach the storage limit, the application automatically deletes the oldest messages.

For more information, see Sending an instant message on page 67.

The Conference screen

The Conference screen displays the participants of the conference, including you, invited participants, and those who have dialed into your conference bridge.

The application displays the phone number or the alias of each participant. You can save the conference participants to a group using the **Save Group** button.



To view the options for the Conference screen, press the menu key on the mobile phone. The available option is **Join Conference**.

To view options for a participant, press the name of a participant:

- **Disconnect**: Use this option to disconnect the participant.
- **Mute**: Use this option to mute the participant.
- **Assign alias**: Use this option to enter a name instead of the phone number, which the screen displays by default. The application retains the alias that you create for future conferences. You can toggle the display between the alias and the phone number of the participant. Only you can see the aliases that you assign.

Icons:

	Tap this option to select the call facility of the participant.
	Tap this option to remove the participant from the conference.
	Indicates the current speaker.
	Indicates that the participant is not speaking.
	Indicates that the participant is on mute.
	Indicates that the conference is locked. Tap this option to unlock the conference.
	Indicates that the conference is unlocked. Tap this option to lock the conference.

If you have concerns about conference capacities or other features, note that hosts the conference bridge and not the mobile phone.

For more information, see Managing your conference bridge on page 50.

The Call Log screen

The Call Log screen provides a list of all calls, including missed, incoming, and outgoing calls. You can clear the call logs if required. You can clear individual call logs or all call logs at once. From the Call Log screen you can also initiate calls, invite participants to your conference bridge, and add contacts to your directory.


The application organizes the logs by date, with the most recent call log appearing first. You can filter the logs according to your preference. Each call log is saved for up to a week, unless manually cleared.

To view additional options for a contact, you can click on that name in the Call Log screen. The options differ for unknown contacts and known contacts.

Known contacts in the Call Log screen have an avatar. The following options are available for known contacts in the Call Log screen:

- Call
- Notify me
- Send IM
- Email
- Add to conference

- Details



The following options are available for unknown contacts in the Call Log screen:

- Call
- Add to conference
- Create contact
- Add to contact

Icons:

	Incoming call.
	Outgoing call.
	Missed call.

Table continues…

	Voicemail (heard).
	Voicemail (unheard).
	Avatar for external contacts.

Chapter 2: Getting started

Application installation

one-X Mobile Preferred for is available for Android mobile phones with OS 2.1 and later.

You can install the application by gaining access to the **Install** option in the application store. Alternatively, you can perform a provisioned installation, whereby you receive an email with the installation and the configuration links. To perform a provisioned installation, note the following:

- Provisioned installations configure most of the application settings.
- You *must* use the mobile phone to activate the email link.

Installing the application on an Android device

Use the following procedure to download and install Avaya one-X Mobile Preferred for on an Android device.

Note:

The Avaya one-X® Mobile application is supported on Android OS 2.1 and later. However, you can use the VoIP feature on your Avaya one-X® Mobile only if you have Android 4.x operating system on your mobile device. Avaya one-X® Mobile is not supported on devices running a custom ROM.

Procedure

1. On your mobile phone, open the Play Store application.
2. Search for and select the application.

   Note:

   When you search for the application, the system displays several options for the Avaya one-X® Mobile family of products. Verify that you select the correct application prior to the installation.
3. Tap **Install**.
4. To accept the permissions for the Avaya one-X® Mobile application, tap **Ok**.
5. Sign in to your Google Checkout account if this is the first time that you are downloading from Android Market.

6. In the Play Store application, select **My apps** and select the Avaya one-X® Mobile application.
7. Tap **Install**.

Configure the application

You must be familiar with the interface and the operations that you can perform on your mobile phone. You must be able to scroll, highlight, and type text using the on-screen keyboard. For more information on how to perform these tasks, see the user guide provided with your mobile phone.

The following sections describe the settings that you must configure before you use Avaya one-X® Mobile.

Configuring the connection to IP Office

Before you begin

To configure the connection between the Avaya one-X® Mobile application and the IP Office server, you must first obtain the following information from your system administrator:

- The name of the Avaya one-X® Portal server.
- Your username and password credentials, which are the same credentials used to access Avaya one-X® Portal.
- The CA certificate used by IP Office.

  Note:

  To install a Trusted CA certificate, see “Installing Certificates”.

  If the IP Office does not use a CA certificate disable the CA certificate. To disable CA certificate, see “Changing Server Certificate Validation settings”.

Note:

You do not have to configure these settings when you perform a provisioned installation.

Procedure

1. The first time that you launch the Avaya one-X® Mobile application, the Settings menu displays automatically. Configure the following settings:
   - Press **Server ID** and enter the host name or IP address of the Avaya one-X® Portal server. Press **OK**.
   - Press **Username** and enter your user ID. Press **OK**.
   - Press **Password** and enter your password. Press **OK**.

Note:

If you need to edit these settings at a later time, you can return to this menu by navigating to the **Home** screen and pressing **Menu > Settings** on the mobile device.

2. Avaya one-X® Mobile connects to the IP Office server automatically.

   When the application successfully connects to IP Office, the triangular status icon changes from red to green.



Configure call control

With Release 9.1 and higher releases, you can use the one-X Mobile Preferred application to change between the two call control options: 3rd-party call control and Voice over IP.

By default, Avaya one-X® Mobile operates in the 3PCC mode.

3rd-party call control (3PCC)

The Avaya one-X® Mobile application operates, by default, in the 3PCC mode. When initiates a 3rd-party call from the mobility client, initiates a 3rd-party call to the mobile phone of the caller and then dials the destination.

In countries where incoming voice calls incur a toll charge, the 3PCC solution does not eliminate the fee for the mobile users, as they still have to pay the cellular charges for incoming calls. In order to reduce toll charges, the mobility client provides users the option to work in the VoIP mode.

Voice over IP (VoIP)

Configuring the Avaya one-X® Mobile application to work in the VoIP mode provides users the option to make calls over Wi-Fi or 3G or 4G data networks. These options eliminate cellular voice charges. Changing to the VoIP mode helps mobile users reduce costs, especially on international calls.

In the VoIP mode, the mobility client has its own extension and performs all call control functions including mid-call features. The mobile user can choose the callback mode when Wi-Fi access is unavailable or when the data connection is not providing adequate voice quality.

For information on enabling the VoIP mode, see Enabling VoIP on page 27.

Enabling VoIP

Use the following procedure to enable Voice over IP (VoIP) mode on one-X Mobile Preferred for . The application operates in the 3PCC mode by default.

Note:

The VoIP feature is available only to users having Power User license.

Procedure

1. Navigate to **Menu** > **Settings** > **Voice over IP** > **VoIP operation mode**.

2. Select one of the options:
   - **Wi-Fi Only**: Select this option to enable VoIP whenever your mobile device is connected over a Wi-Fi network.
   - **Always**: Select this option to enable VoIP for all data connection types that are active.
   - **Never**: - Select this option to disable VoIP mode.
   - **Wi-Fi Only With Mobile Fallback**: - Select this option to enable auto-switching call facility from VoIP to Mobile when Wi-Fi connectivity is lost. The call facility switches back to VoIP when Wi-Fi connectivity is resumed.

     Note:

     With the **Wi-Fi Only With Mobile Fallback** mode selected, when the call facility is set to VoIP and Wi-Fi connection drops, the application automatically switches the call facility to Mobile. When the Wi-Fi connectivity resumes, the application switches the call facility back to VoIP. If you change the call facility manually to anything else, the auto-switching is stopped. You can resume the auto-switching by setting the call facility back to VoIP.

     For example, when John selects the **Wi-Fi Only with Mobile Fallback** option:

     - In a Wi-Fi zone: The application sets the call facility on the phone to VoIP.
     - In a non-Wi-Fi zone: The call facility switches automatically to the mobile option.

     Using the **Wi-Fi Only with Mobile Fallback** option, John saves on airtime minutes when he is in a Wi-Fi zone. In a non-Wi-Fi zone, John uses the mobile phone because the data plan might not be large enough or reliable enough to make a VoIP call.
3. Tap the **Call Facility** icon.
4. Select **VoIP**.
5. Select one of the call back options. This is the number where you receive a call back if a VoIP call cannot connect for any reason.
6. Tap **OK**.

   The Phone icon on the Home screen turns to green when the client is registered to .

Configuring user call monitoring

You can use one-X Mobile Preferred for on your Android phone to interact with all incoming and outgoing calls. Using the User call monitoring feature, you can interact with the following types of calls:

- Calls made or received through deskphone, softphone, or Flare
- Calls established using the one-X Mobile Preferred for application or Avaya one-X® Portal.
- Calls answered on mobile through mobile twinning.

Procedure

1. On your mobile device, tap **Menu** > **Settings** > **Call Monitoring Mode**.

2. Select one of the options:
   - **VoIP calls only**: Select this option to enable User call monitoring only for VoIP calls.
   - **All my calls**: Select this option to enable User call monitoring for all your calls.

   All my calls is selected by default.

Next steps

For more on Use call monitoring, see Handling user call transfers on page 48.

Configuring enterprise dialing

The enterprise dialing feature determines whether Avaya one-X® Mobile integrates with the native dialing application on the mobile phone. If you allow Avaya one-X® Mobile to integrate with the native dialing application on the mobile phone, Avaya one-X® Mobile intercepts and routes calls using the enterprise server rather than through the cellular network.

In addition, enterprise dialing hides the mobile identity of the caller, which allows you to protect your privacy if you are using your personal mobile phone for business purposes.

For added flexibility, you can also configure a dial plan so that the application routes enterprise calls according to the rules that you specify. Configure dial plan rules to manipulate called numbers before the application transfers them to the PBX.

Note:

- Avaya one-X® Mobile must be connected for the dial plan function to work.
- You can configure dial plans only within the application and not within the settings of the mobile phone.
- The contacts in the mobile phone are not merged with the contacts in the Avaya one-X® Mobile application.

Procedure

1. On the mobile phone, navigate to the Home screen and press the menu key.
2. Tap **Settings**.
3. Tap **Enterprise Dialing**, and tap **Mode**.
4. Tap one of the following options:
   - **Off:** No integration.
   - **On:** Use integration.
   - **Prompt:** Prompt to use which dialer each time.
   - **Dial Plan:** Use the enterprise dial plan.
5. To configure the rules for enterprise dialing, return to the **Settings** menu.
6. Tap **Dial Plan**.

Avaya one-X® Mobile intercepts and routes only those calls that match the dial plan rules.

7. Press the menu key on the mobile phone and tap **Add new rule** to reveal an inactive rule.
8. Tap the inactive rule and configure the following options:
   - **Active:** Select the check box to enable the rule.
   - **Prefix:** Tap and type the prefix for calls that you want Avaya one-X® Mobile to intercept and route.
   - **Suffix length:** Tap and select the number of characters that follow the prefix.
   - **Characters to absorb:** Tap and select the number of characters.
   - **Characters to insert:** Tap and type the characters to insert before the prefix.
   - **Dial plan mode intercept:** If you choose **Prompt** or **Dial Plan** as the enterprise dialing mode, the application enables this option automatically.
9. To return to the Dial Plan screen, press the back button on the mobile phone.

   The screen displays that Rule 1 is now active.
10. To add another rule, press the menu key on the mobile phone and tap **Add new rule**.

    You can also edit, delete, reorder, and reconfigure existing rules.

Example

You might like to manipulate all long-distance calls but not local calls before the application routes the call through the call server. If the area code is `613`, your dial plans would consist of the following:

1. `1613+ - prefix 1613, suffix 7, rule is not active.`
2. `1+ - prefix 1, suffix 10, rule is active.`

The above two rules will manipulate all "1+" calls except 1613+ calls.

Configuring the notify me feature

If someone in your contacts list is unavailable, you can use the **'Notify Me' feature** option to monitor the availability of that contact. When you set the **'Notify Me' feature** option for a contact, Avaya one-X® Mobile notifies you when the presence status of the contact changes.

For information on using the notify me feature for a contact, see Using the notify me feature on page 40.

About this task

Use the following procedure to configure the **'Notify Me' feature** option.

Procedure

1. On the mobile phone, navigate to the Home screen and press the menu key.
2. Tap **Settings**.
3. Tap **'Notify Me' feature**.

4. Tap **Mode** .
5. Select one of the following options:
   - **Continuous:** To receive notifications as the availability of the contact changes. You continue to receive updates until you disable the option for that contact.
   - **One time:** To receive a notification as the availability of the contact changes. You do not receive updates after the first notification.

Setting preferences for notifications

The Avaya one-X® Mobile application notifies you according to your preferences. For example, the Avaya one-X® Mobile application notifies you when you receive new voice mails or instant messages, or when users join your conference. You can also receive notifications when your connection to changes.

About this task

Use the following procedure to configure your notification preferences.

Procedure

1. On the mobile phone, navigate to the Home screen and press the menu key.
2. Tap **Settings > Notifications**.
3. Tap **Notification Profile**, and choose your preferred method of notification. The options are:
   - **Vibration and Sound**
   - **Vibration only**
   - **Sound only**
   - **No Vibration or Sound**
4. From the **Notifications** menu, select the check box next to the options for which you want to receive a notification. The options are:
   - **Instant Message**
   - **Voicemail**
   - **Missed Calls**
   - **Conference Join**
   - **Conference Leave**
   - **Server Connection**
   - **Location Tracking**
   - **VoIP Registration**

Configuring GPS information

If you enable geo-presence, Avaya one-X® Mobile publishes your geographic location to other users when the users request for that particular information.

Before you begin

To use the geo-presence feature, you must first enable GPS on your mobile phone.

- Navigate to the Home screen and press the menu key, tap **Settings**, and select the **Publish Location** check box.

About this task

Important:

If a user observes your geo-presence information, the GPS updates provided by your mobile phone are frequent, thereby shortening the battery life. The level of information that you choose to publish also affects the battery usage on your mobile phone. For example, when you choose **Maximum**, the battery usage on your mobile phone increases because the application updates the information frequently.

Use the following procedure to control the level of geo-presence you want to share with other users.

Procedure

1. To view the list of available locations in the application, navigate to **Settings** > **Location Precesion**.
2. Tap the appropriate location from the list. The options are:
   - **City:** Displays the city and the state or the province of your current location.
   - **Neighborhood:** Displays only the country, the city, and the state or the province of your current location.
   - **Street:** Displays the street address and the neighborhood information for your current location.
   - **Maximum:** Displays your current location in detail, including the nearest street.

Deleting GPS locations

If you have published your geo-presence location to other Avaya one-X® Mobile users, you can delete the information from the mobile phones that have received the data. For example, if you disable geo-presence, your last published location remains available to contacts who requested for that particular information. You can delete this information so that when a contact requests for the information, the mobile phone displays the `No information is available` message.


Procedure

1. In the Avaya one-X® Mobile application, navigate to **Settings** > **Location Precesion**.
2. Tap **Clear Locations**.

Enabling or disabling mobile twinning

The mobile twinning feature in Avaya one-X Mobile Preferred for lets you twin an external phone with an internal extension. When you receive a call on your extension, the twinned number also rings. You can receive the call either on the extension or the twinned number.

In previous versions, the Call Facility button was used to control how calls were placed. In this version, the Call Facility button also controls how the calls are received. When you tap the Call Facility button on the home screen, the following pop-up screen appears:



No.	Description
1	The fields located here control how the application places calls. This does not affect mobile twinning.
2	The fields located here control how incoming calls are received. This effectively controls mobile twinning.
3	Selecting this button disables Mobile Twinning.
4	Selecting this button twins incoming calls to mobile phone.


Table continues…

No.	Description
5	Selecting this button twins incoming calls to home phone.
6	Selecting this button twins incoming calls to any other number you specify.

Note:

The mobile twinning feature is not available for you by default. Your administrator must enable the feature for your extension before you can start using the feature. When VoIP is enabled on the application, it rings on all incoming calls irrespective of mobile twinning setting.

Mobile Twinning is synchronized between Avaya one-X® Mobile and Avaya one-X® Portal.



Note:

The mobile twinning feature when enabled, the application will present the gsm call and ignore the VoIP call if both come simultaneously.

About this task

Use the following procedure to enable or disable mobile twinning from Avaya one-X® Mobile:

Procedure

1. Tap the **Call Facility** button on the home screen.
2. Perform any one of the following, as required:
   - To enable mobile twinning, tap to select any of the following radio buttons that appear below **Receive calls on**:
     - **Mobile**
     - **Home**
     - **Custom**
   - To disable mobile twinning, tap to select the **Work Only** radio button.

Configuring DND settings

You can configure the Do Not Disturb (DND) feature on your Avaya one-X® Mobile phone to stop your phone from ringing for incoming calls.

About this task

Use the following procedure to enable the DND feature:

Procedure

1. On the mobile phone, tap the menu key while Avaya one-X® Mobile application is open.
2. Tap **Settings**.
3. Select the **Do Not Disturb** check box.

   The DND icon appears on the Avaya one-X® Mobile home screen.

Next steps

To disable DND settings:

1. Tap the DND icon on the home screen.
2. Tap **OK** when the application prompts you with the message Do you want to disable the 'Do Not Disturb' feature.

   Alternatively, you can tap Settings on the mobile device and clear the **Do Not Disturb** check box.

Viewing support information

Configuring the quality improvement option

About this task

Use this procedure to configure the quality improvement option so that Avaya can collect quality related product data.

Note:

Avaya collects data for quality improvement purposes only. No personally identifiable information is tracked.

Procedure

1. In the Avaya one-X® Mobile application, go to the Settings screen.
2. On the Settings screen, move the **Help improve the app** slider to the left to disable the feature and to the right to re-enable the feature.

   Note:

   By default **Help improve the app** is enabled.

Viewing emergency calls disclaimer

About this task

The Avaya one-X® Mobile application displays the end user license agreement (EULA) and emergency calls disclaimer as soon as you finish installing or reinstalling the application.

Important:

Avaya strongly advises to not use the Avaya one-X® Mobile application to make an emergency call.

Procedure

In the Avaya one-X® Mobile application, navigate to **menu** > **Settings** > **Emergency Calls.**

The Emergency Calls screen displays the following text: `Do not use this application to make an emergency call.`

Changing the password

You can change the password when Avaya one-X® Mobile is connected to the primary server only. If you change the password when Avaya one-X® Mobile is connected to the secondary server during a failover scenario, the new password is not retained. This results in failed login attempts when Avaya one-X® Mobile is connected back to the primary server.

Procedure

1. On the Avaya one-X® Mobile application screen, navigate to **Menu** > **Settings**.
2. On the Settings screen, tap **Change Password**.
3. On the **Change Password** screen, type the password details.
4. Tap **Confirm**.

Change Password screen field descriptions

Name	Description
Current Password	Type the current password
New Password	Type a new password
Confirm New Password	Re-type the new password

Enable the widget

On the Android OS, an Avaya one-X® Mobile widget is available to display on the home page of your mobile phone.



The widget uses notification icons to indicate the number of new communications you have received through the application. For more information about enabling a widget, refer to the user guide that came with your mobile phone.

Self-administration on Avaya one-X® Portal

Use Avaya one-X® Portal to specify the conference bridge number that the Avaya one-X® Mobile application must use for conference calls. You can also specify personal and mobile phone numbers, which propagate to the mobile phone and vice versa.

In addition, you can use Avaya one-X® Portal to enable the phone status and the calendar information for contacts who want to view your presence.

Configuring the conference bridge

To set your conference bridge number, log on to Avaya one-X® Portal and perform the following steps:

- Select **Configure > Telephony**.
- Enter your personal conference bridge number. Contact your system administrator to determine which conference bridge number to use.

Enabling phone status

You can select whether you want your current phone status to be available to other contacts when the contacts request for that information. When you enable your phone status, your contacts can use the Avaya one-X® Mobile application to view whether you are currently on the phone. To set the availability of your phone status, log on to Avaya one-X® Portal and perform the following steps:

- Select **Configure > Telephony > IM/Presence**.
- Select **Advertise on call status**.

Enabling calendar information

You can select whether you want your calendar status to be available to other contacts when the contacts request for that information. When you enable your calendar status, your contacts can use the Avaya one-X® Mobile application to view your meetings scheduled for the current day, including the time at which the meetings occur.

- Select **Configure > Telephony > IM/Presence**.
- Select **Advertise calendar status**.

Chapter 3: Managing Status Information

Managing status information

The Avaya one-X Mobile Preferred for IP Office lets you set information about your own availability and view information about the availability of your contacts. The application is also capable of integrating with your Microsoft Office Outlook calendar, and is capable of providing status updates based on your scheduled appointments.

Presence and status

You can determine a user's availability on the network, also known as presence, in one of two ways:

- By an icon that changes color to reflect the current status of the user.

  or
- By a text message entered by the user.

The presence icons are green, yellow, and red to quickly identify your presence status by color. Each color-coded icon has a field where you can enter status text.

Your presence, which you can set on any screen, is available to your contacts. Avaya one-X® Mobile displays your presence information as well as the presence information of your contacts.

For information about viewing the presence of your contacts, see Monitoring the availability of your contacts on page 39.

Integration with your calendar

If you use Microsoft Office Outlook or Microsoft Office Outlook Web Access, Avaya one-X® Mobile can use data from your calendar to update your status information. The application uses the start and end times of meetings in your calendar to provide the following status information:

- When you have a meeting scheduled in your calendar, the Avaya one-X® Mobile sets your status to **Busy** five minutes prior to the meeting, and displays the message **Starting a meeting at <*time*>.**
- When the meeting begins, your status message is updated to **In a meeting until <*time*>**.
- After the meeting ends, your status changes to **Available**.
- When your calendar indicates that a meeting is scheduled for an entire day, your status message changes to **In an all-day meeting**.

If you have already entered a text status, calendar messages append to your text status. For example, if you enter a text status of **At work** and you are in a meeting until 3 p.m., Avaya one-X® Mobile updates your text status to **At work — in a meeting until 3 p.m.**

Avaya one-X® Mobile also provides calendar information for your contacts. For more information, see Monitoring the availability of your contacts on page 39

Calendar information is only available if your system administrator configures it to be available.

Monitoring the availability of your contacts

Avaya one-X® Mobile provides several options for viewing the availability of your contacts.

Presence information:

There are several places within the Avaya one-X® Mobile application where you can view the presence of your contacts:

- On the Contacts list, where presence information is displayed for internal contacts.
- On the Conference screen, where presence information is displayed for internal conference participants. Presence information is not available for external participants.
- On the Voicemail screen, where presence information is displayed for the sender of the voicemail message.

On each of these screens, a color-coded icon appears to the left of the contact's name. The text status entered by that contact is displays below his or her name.

Presence information is available for both system contacts and personal contacts, such as gmail contacts. However, note that personal contacts added to the “Personal” directory in Avaya one-X® Portal appear duplicated on your mobile phone if the name matches a contact that already exists in the “System” directory, and that this duplicated contact will not have presence information available. To avoid this kind of duplication, use the correct method for adding a system contact to the “Personal” directory in Avaya one-X® Portal. The correct method is to use the “System” directory's **Add to group** button. For more information, see the Avaya one-X® Portal documentation.

The Follow feature:

When you want to reach contacts whose presence status indicates that they are not available, you can use the Follow feature to automatically monitor their availability. When you set the Follow feature for a contact, the Avaya one-X® Mobile notifies you when the presence status of the contact shows an improvement in availability. For example, the Follow feature notifies you when the presence status of the contact changes from **Do Not Disturb** to **Available**. An icon showing footsteps displays next to the name of the contact to indicate that the feature is enabled.

There are two options for using the Follow feature:

- Automatically stop following a contact after you have been notified of a status change.
- Continue to receive notifications about status changes until you choose to stop following a contact.

For more information about configuring the Follow feature, see Configuring follow mode on page 30.

Calendar information:

You can view calendar information for your contacts. The Avaya one-X® Mobile displays the meetings and appointments scheduled for the current day.

Phone status:

You can view whether a contact is currently on the phone.

Setting your status

The Status bar provides an area where you can indicate your presence and set a status message. The Status bar is available on all screens in the Avaya one-X® Mobile application.

About this task

The status area includes color-coded icons to reflect your presence, as well as a text field for your status message. You can enter a new status message in the text field, or reuse a recent status message. Avaya one-X® Mobile retains your five most recently used status messages.

Procedure

1. In the Status bar, tap the status text area.

   The application displays a dialog box.
2. Tap a color-coded icon.
3. To change the status message, choose one of the following options:
   - To display the keyboard and enter a status, tap the text field. As you type letters, the application displays the recent status messages that match those letters. Tap a status message or enter a new status message.
   - To enter your status using voice recognition, tap the microphone button on the keyboard. After you finish speaking, click **OK** to confirm that the status is correct.
   - To display the **Edit** menu, long-press the text field. You can use the **Edit** menu to select, cut, copy, and paste text in your status message. You can also use the **Edit** menu to add words to your dictionary.

     Select an option from the **Edit** menu, and then tap the text field to reveal the keyboard and continue editing your status message.

Using the notify me feature

If someone in your contacts list is unavailable, you can use the **'Notify Me' feature** option to monitor the availability of that contact When you set the **'Notify Me' feature** option for a contact, Avaya one-X® Mobile notifies you when the presence status of the contact changes. For example, the application notifies you when the presence status of a contact changes from **Do Not Disturb** to **Busy** or from **Busy** to **Available**.

About this task

When the presence status of a contact that you are monitoring changes, you receive an update in the notification bar at the top of your screen and you receive an instant message.

Procedure

1. On the Contacts screen, tap the name of the contact whose availability you wish to monitor.
2. Tap **Notify me**.

The application displays a *footsteps* icon next to the name of the contact.

3. (Optional) To stop getting notifications, tap **Don’t notify**.

Viewing calendar information

Use the Avaya one-X® Mobile application to view whether the selected contact is in a meeting at a given point of time.

Procedure

1. On the Contacts screen, tap the name of a contact to open a communication screen for that person.
2. Tap the **Details** icon.

   The Avaya one-X® Mobile application displays a message indicating whether the selected contact is in a meeting.

Viewing the phone status

You can view whether a contact is currently on the phone.

Procedure

Choose one of the following methods:

- To open a communication screen for a contact, on the Contacts screen, tap the forward arrow corresponding to the contact.

  Note:

  If the contact is on the phone, then the application displays a highlighted phone icon on the communication screen.

- On the Contacts screen, view the entry for a contact. If the contact is on the phone, the application displays a phone icon in red color next to the name of the contact.

Chapter 4: Handling Calls

Making calls

When you use Avaya one-X® Mobile to initiate a call, by default, the application instructs to dial the phone number for your current location. After you pick up the phone at your location, Avaya one-X® Mobile dials the number that you want to reach. This approach means that calls are routed through the PBX using 3rd-party call control (3PCC). If you select VoIP mode in lieu of 3PCC mode, the Avaya one-X® Mobile application handles the call instead of .

In either mode, you can:

- make, receive, and end calls
- access touch tone keys during active calls
- perform supervised and unsupervised transfers

Note:

While you are on a 3G call, you may not be able to access some call features or send instant messages. Some mobile devices, and some service providers, limit data signalling during a 3G call.


The following sections describe how to set your location information and how to initiate calls.

Setting your call facility

Before you can place a call, you must specify the phone number where the Avaya one-X® Mobile application can locate you. For example, if you normally place calls through your deskphone, you can choose to establish a call using a mobile phone or a phone located in a hotel room when you are travelling.

Typically, your call facility is the mobile device where you installed the Avaya one-X® Mobile, but you can set your call facility as required. You can specify the phone that you prefer to use for your calls and update the number as your call facility changes.

If you try to place a call but you have not set your call facility, a wizard guides you through the procedure:



About this task

Press the **Call Facility** icon in the Status bar to set your call facility:

- The default call facility is **Mobile**.

  The application automatically detects the **Mobile** number from the SIM card within the device.

Procedure

1. In the Status bar, press the **Call Facility** icon to open a menu.
2. Select one of the following call facilities from the menu:
   - **Mobile phone:** The mobile phone number is set in the Avaya one-X® Mobile client or in Avaya one-X® Portal.
   - **Work phone:** The work phone number is set by your system administrator and is not configurable.
   - **Home phone:** The home phone number is set in the Avaya one-X® Mobile client or in Avaya one-X® Portal.
   - **VoIP**: This is the phone number or extension of the device from which you have logged in to Avaya one-X® Mobile client. This phone number is the same as the extension configured by your system administrator.
   - **Custom phone number:** The Custom phone number can be set only in the Avaya one-X® Mobile client. You cannot use internal extensions as your Custom phone number. Avaya one-X® Mobile displays an `Operation Failed` message if you set an internal extension as your Custom phone number.

After you select a call facility, the Status bar shows an icon specific to that call facility.

3. To change the phone number for the active call facility, tap the **Call Facility** icon in the Status bar and select **Set phone number** from the menu. Proceed to the next step.

   To clear the phone number for the active call facility, tap the **Call Facilty** icon in the Status bar and select **Clear phone number** from the menu. The application provides a confirmation message and returns to the home screen.

4. Input the new number in the text field. To include a prefix, enable the **Phone system requires a prefix** checkbox and enter the prefix number in the **Prefix** field.
5. When you are satisfied, press **OK** or **Save** depending on your device.


Initiating a call from the Dialpad

Use the following procedure to initiate a call from the Dialpad that appears on the status bar. Avaya one-X® Mobile places the call using the call facility you have selected.

Procedure

1. Press the Dialpad icon on the status bar.

   The Dialpad screen appears.



2. Tap the phone number on the Dialpad or select a previously dialed phone number.

   When you start typing the digits, the application displays the last dialed phone numbers. The application lists the last 20 dialed phone numbers. The application does not list the outgoing calls that are not initiated from the dialpad.

3. Tap the call icon.

   The call is placed using the selected call facility.

Initiating a call from the contacts list

Procedure

1. Use any of the following methods to initiate a call from the contacts list:
   - Dial the extension or the phone number using the integrated dialer.
   - Tap a name on the contacts list to view the options available for that contact and tap the phone icon .
2. (Optional) To add the contact to a conference, tap the add to conference icon .
3. (Optional) To view the details of a contact, tap the information icon .

Initiating a call from an instant message

Use the following procedure to reply to an IM by calling the sender.

Procedure

1. On the mobile phone, navigate to the Instant Message screen and tap the instant message.

   The application displays a communication screen.
2. To initiate a call, tap the phone icon.

Initiating a call from the call log

Use the following procedure to initiate a call from the Call Log screen.

Procedure

1. On the Call Log screen, tap the name of the contact that you want to call.

   The application displays a communication screen for that contact.
2. Tap the **Call** option.

Using the integrated dialer

Avaya one-X® Mobile provides an integrated dialer that you can use to place calls to contacts in your personal directory or in your corporate directory. You can also use the dialer to call external contacts.

Before you begin

Configure rules in **Settings** > **Dial Plan**. For more information, contact your system administrator.

Procedure

1. To start the dialer, navigate to the Contacts screen and tap the integrated dialer button.
2. Type the complete number.
3. To initiate a call, tap the phone icon .

Initiating an e-mail from the Contacts list

Use the following procedure to initiate an e-mail from the Contacts list. If the contact has no e-mail address configured, a message appears to that effect. If the contact has a valid e-mail address configured, then you can choose a preferred e-mail application and use it to send that contact an e-mail.

Procedure

1. Press the name of the contact in the Contacts list.
2. Select the **Email** option.

   The preferred e-mail application of your mobile device opens.

Making a selection

If you tap a contact in the contacts list, you can view the **Select** icon. Use the **Select** icon to select the contact. Tap additional contacts to add them to the selection.

Alternatively, you can long-press a contact to select that contact. Tap additional contacts to add them to the selection.

The application displays the number of selected contacts at the top of the screen. For example, `1 selected`. If you leave the Contacts screen without performing an action, the contacts remain selected.

Procedure

1. On the Contacts screen, tap the contact that you want to select.
2. Tap **Select**.
3. To select multiple contacts, tap the contacts that you want to select.

   The application displays the number of selected contacts at the top of the screen.
4. (Optional) To set up a conference for all the selected contacts, tap **Conference**.
5. (Optional) To view the remaining options, tap the **Options menu** icon.

   The options available for the selected contacts are:

   - **Conference**
   - **Send IM**

- **Email**
- **Save to Local Group**
- **Locate**

Using Avaya one-X® Mobile to call any number on your phone

Before you begin

About this task

Use Avaya one-X® Mobile to call any phone number from your smart phone. You can call a number listed in native contacts, in the calendar, on an web page, in a message, or an email, and so on.

Procedure

1. Tap a number on any of the applications on you phone.

   Your smart phone prompts you to select an application to complete the call.

2. Select Avaya one-X® Mobile.

Configuring the setting for reading out the name of the caller

About this task

Use this procedure if you want the application to read out the name of the person who is calling you. By default, the application disables this setting.

Procedure

1. On the Avaya one-X® Mobile application screen, navigate to **Menu** > **Settings**.
2. In the Voice Announcements area, move the **Speak Caller Name** slider to the right.
3. Tap **Done**.

Transferring 3rd-party calls

You can use the 3rd-party call transfer feature to transfer the calls you receive when using Avaya one-X® Mobile as a 3rd-party call controller.

Procedure

1. When you have an active call, tap the **Transfer Call** button Avaya one-X® Mobile screen.

2. Use either of these options:
   - Select the destination number from your Contacts.
   - Use the dialpad to dial the destination number.
3. On the Transfer Call screen, tap the **Transfer** button.

Moving a call to other phones

Procedure

1. To transfer a call, on the mid-call control screen, tap the **Calls** icon.

   The mobile phone displays the Active call list screen.
2. On the Active call list screen, tap the **Move calls** icon.

   The mobile phone displays a Move Calls to dialog box.
3. In the Move Calls to dialog box, select from the following options:
   - **VoIP**: This is the phone number or extension of the device from which you have logged in to Avaya one-X® Mobile client. This phone number is the same as the extension configured by your system administrator.
   - Mobile: The mobile phone number is set in the Avaya one-X® Mobile client or in Avaya one-X® Portal.
   - Home: The home phone number is set in the Avaya one-X® Mobile client or in Avaya one-X® Portal.
   - Work: The work phone is set by your system administrator and is not configurable.
   - Custom: The custom phone number can be set only in the Avaya one-X® Mobile client.
4. Tap **OK**.

Related links

Setting your call facility on page 42


Handling user call transfers

Consider you are in your car and you need to make a sales call from your Avaya one-X® Mobile to a potential customer. You make your pitch and close the sale and would like to transfer the call to your administration to complete the transaction. To handle a situation like this, you need a feature that provides you the flexibility of handling all your calls, be it office or external, from one application. The User call monitoring feature can help you in carrying out all the activities without using any other device or application.

If you have set your Call monitoring mode to All my calls, all calls involving you appear on the Active call tab. For information on configuring your application for User call monitoring, see Configuring

user call monitoring on page 28. During an active call, you can tap the Active call tab to view the following details of ongoing calls:

- Display name and extension number of the far end phone
- Avatar of the far end phone
- Current state of the call
- Call timer
- Device used at the near end



Procedure

1. When you have an active call, tap the **Transfer Call** bar on your Avaya one-X® Mobile screen.

   The application displays the Contacts screen.

2. Select the Contact whom you want to transfer the call.

   Application displays a pop-up asking you to select the number you want to call.

3. Select the number you want to call.

   The call is transferred to the selected number of the contact. These transfers are unsupervised transfers.

Chapter 5: Making conference calls

Managing your conference bridge

You must have a conference extension configured in Avaya one-X® Portal in order to host and manage conference calls. Note that IP Office hosts the conference bridge and not the mobile device.

From the conference screen you can join your own conference bridge, mute or unmute participants, enter aliases for participants, and disconnect participants. You can manage your conference using the visual indicators on the Conference screen. The visual indicators let you see the following:

- Who is connected to your conference bridge.
- Which participants are muted or unmuted.
- Whether the conference is locked or unlocked.
- Presence information for conference participants.
- Whether participants are internal or external contacts. An icon of a telephone pole indicates an external contact.

The phone number or alias of each participant is shown. If the participant is on your contacts list, his or her avatar will display. An icon of a telephone pole indicates an external caller.

It is possible to save the conference participants to a group using the **Save Group** option.

Icons:

The following icons appear on the Conference screen.

	Press this button to select the call facility of the participant.
	Press this button to remove the participant from the conference.
	Indicates the current speaker.
	Indicates that the participant is not speaking.

Table continues…

	Indicates that the participant is muted.
	Indicates that the conference is locked. Press this button to unlock the conference.
	Indicates that the conference is unlocked. Press this button to lock the conference.

Adding conference participants

Use your Contacts list to add participants to a conference call. You can add individual contacts to a conference call, you can add multiple contacts at once, or you can establish a conference for a particular group or groups.


When you add participants to a conference, the participants appear on the Conference staging screen. Note that the list of participants includes yourself. To remove a participant from the conference list, see Disconnecting participants on page 55.

To start the conference, see Starting a conference on page 52.

Use the following procedures to add participants to both new and ongoing conferences.


Procedure

1. To invite an individual from your Contacts list to a conference call, press the name of the contact to open a communications screen for that contact. Press the **Add to conference** icon:

2. To add multiple contacts to a conference call, long-press a contact.

   A selection bar appears at the top to indicate that the contact is selected while you press other contacts that you want to include in the selection.

   The application adds the selected contacts to a virtual group which you can add to the conference by pressing the **Conference** icon in the selection bar:

You can deselect contacts by pressing their entry a second time.


In addition, you can add local groups to your selection and thereby create a conference call for all members of that group, including any other selected contacts. You should create and use local groups if you meet with a team regularly, and when you want to save time setting up a conference.

3. To add external participants to a conference call, press the integrated dialer and perform the following steps:
   a. Enter a phone number in the **Dial number** field.
   b. Press the **+** icon on the keyboard to add the number to a **Dialed Numbers** list.
   c. Long-press the dialed number to add the contact to a selected group.

      Add any additional participants to the selected group as desired.
   d. Press the **Conference** icon on the selection bar.

Starting a conference

After adding contacts to the conference, the participants appear in the Conference staging screen. For more information, see Adding conference participants on page 51.



The staging screen contains a **Save Group** button. Pressing the **Save Group** button saves all the conference participants to a group. This group appears in the **My Local Groups** section of the Contacts list, which you can select in the future so that you do not have to manually add each participant again.

During the conference, the staging screen is divided by participants **On the call** and participants who have **Left the call**. You can press the names of participants on the call to view the following options:

- **Disconnect:** Disconnect the participant.
- **Mute:** Mute the participant.
- **Assign alias:** This option allows you to enter a name instead of the phone number that displays by default. The application retains the alias that you create for future conferences. You can toggle the display between the alias and the participant's phone number. Note that only you can see the aliases that you assign.

Procedure

1. To start the conference call, press the **Start Call** button.

2. After the conference begins, you can invite additional participants. See Adding conference participants on page 51.

Joining a conference in progress

You might want to rejoin a conference that you left in progress. Use the following procedure.

Procedure

1. Navigate to the Conference screen.
2. Press the **Menu** button on the device.
3. Select the **Join conference** option from the menu.

Locking and unlocking a conference

You can lock and unlock conference calls that are in progress. Use the lock option when you want to prevent new participants from joining the conference.

Procedure

1. To lock a conference, press the unlocked padlock icon:

   The icon turns red indicating that the conference is now locked. New participants cannot join the conference.
2. To unlock the conference, press the locked padlock icon:

   The icon turns grey indicating that the conference is now unlocked. New participants can join the conference.

Muting participants

As the conference host, you can mute individual participants or you can mute all participants.

About this task

When you mute and unmute conference participants, the microphone icon next to the participant's name indicates the microphone status. The icon next to a muted participant looks like a microphone with a line through it:



Procedure

Choose one of the following options:

a. To mute an individual participant, on the conference screen, tap **Edit**, select a participant and tap **Mute**.

   Perform the same steps to unmute the participant.

b. To mute all participants, on the Conference screen, press the More Menu button and tap **Mute**.

   The application mutes the conference owner.

   Perform the same steps to unmute all participants.

Disconnecting participants

Use the following procedure to disconnect participants from your conference bridge, either individually or altogether. Use the same procedure to remove yourself from the conference. When you remove a participant from a conference call, or when the participant leaves the call, the participant appears in the **Left the call** section.

Procedure

1. On the Conference screen, determine the participant you want to disconnect from the conference.

   The microphone icon of the present speaker appears blue.

2. Choose one of the following:

   - Long-press the name of the participant and select **Disconnect** from the menu.

     or

   - Press the **End call** button and confirm the request. Pressing the **End call** button ends the entire conference, which disconnects *all* participants.

Starting an adhoc conference

Before you begin

Ensure that:

- There is more than one in-progress call.
- Calls are either in Active or Hold state.
- All calls are not in Hold state.

About this task

Use this procedure to start an adhoc conference while on an active call. To avoid issues with adhoc conference calls, Avaya recommends that there is:

- No ongoing meet-me conference call
- Only one adhoc conference call

Note:

You cannot merge two or more VoIP adhoc conferences.

Procedure

While on the active call, tap **Conference**.

The application adds the participants of the in-progress calls to the conference.

Chapter 6: Using the Events history

About Events history

Avaya one-X Mobile Preferred for IP Office R 9.0 provides an Events tab on the main screen. You can tap the Events tab to view the Events screen. The Events screen by default displays all events. However, you can chose to view a specific type of event by filtering the events. For more information, see Filtering the Events on page 58. You can also tap an event to perform actions related to the selected event. The actions you can perform by selecting an event varies according to the type of event.

Event type	Actions you can perform
Voicemail	• **Call** • **Play** • **Send via Email** • **Mark as unheard** • **Delete**
Call history for Contacts	• **Call** • **Notify Me** • **Send IM** • **Send Email** • **Add to conference** • **Details**
Call history for Contacts not in your phone book	• **Call** • **Add to conference** • **Create contact** • **Add to contact**

Filtering the Events

Use the following procedure to filter the events. You can filter the events history to view the following:

- New Events
- Missed Calls
- Incoming Calls
- Outgoing Calls
- Voicemail Inbox

By default, the filter displays all events.

Procedure

1. On the Events screen, tap **All Events**.

   The application displays a drop-down menu listing the options.

2. Select the event you want to view.

   The Events screen displays all the events for the selected type of events.

Clearing the Events history

Use the following procedure to clear history for Missed Calls, Incoming Calls, and Outgoing Calls.

Procedure

1. Navigate to the Events screen, and select a type of event.
2. To clear the selected event history, tap **Clear**.

   The application displays a confirmation dialog.

3. To clear the events, tap **Yes**.

Configuring notification settings for missed calls

Procedure

1. Navigate to **Menu** > **Settings** > **Notifications**.
2. Tap **Missed Calls** and ensure that the corresponding check box is selected.

Chapter 7: Managing VoIP calls

About the VoIP feature

The Avaya one-X Mobile Preferred for application supports Voice over Internet Protocol (VoIP) calls. VoIP is a set of technologies and transmission techniques that are used to deliver voice over IP networks, such as the Internet.

You can make and receive VoIP calls using the Avaya one-X® Mobile application. Configuring the Avaya one-X® Mobile client to work in VoIP mode gives you the option to make calls over Wi-Fi/3G/4G data networks, thus eliminating cellular voice charges. Switching to VoIP mode helps mobile users reduce costs, especially on international calls.

In VoIP mode, the mobility client registers the user extension on and performs all call control features including mid-call features. You can choose call-back mode when Wi-Fi access is unavailable or when the data connection is not providing adequate voice quality. By default, VoIP calling is disabled and needs to be enabled using the application. For information on enabling VoIP calling, see Enabling VoIP on page 27.

VoIP simultaneous registration

Avaya one-X Mobile Preferred for can simultaneously register on with other devices such as the Desk phone, Flare, and Soft phone. However, either Avaya one-X® Mobile for iPhone or Avaya one-X® Mobile for Android can register on at the same time.

Prerequisites and supported devices

Prerequisites

The VoIP feature will be available on the Avaya one-X® Mobile application when:

- The mobile application is connected to 9.0 or later.
- The VoIP feature is enabled on the server/
- Users must have Power User license.

Supported devices

The VoIP feature is certified to work and provide acceptable acoustic performance for the following devices only:


- Samsung Galaxy S3 running Android version 4.0 or later
- Samsung Galaxy S4 running Android version 4.0 or later

- LG Optimus E975 running Android version 4.0 or later
- HTC One-S running Android version 4.0 or later




The VoIP feature may work on other devices but users may encounter performance degradation, lower voice quality, or other problems.

Status indicators for VoIP

When VoIP is enabled, but is having difficulty registering with the server, the mobile application's connection status icon in the notification bar turns yellow. At such times, the VoIP registration issue indicator provides more information about possible VoIP related issues.




The Avaya one-X® Mobile application displays VoIP status information on the **Active Call** tab icon as follows:

Icon	Description
	VoIP is enabled and registered
	VoIP pre-requisites met but VoIP disabled
	VoIP pre-requisites not met

Error messages for VoIP

The VoIP registration issue indicator on the Avaya one-X® Mobile user interface provides more information about possible VoIP related issues. Tapping the indicator provides VoIP registration status as well as an Error code as shown here:



Following are a few Error codes that appear when you try connecting to server:

Error Code	Description
403	Indicates that another mobile application is already registered on the server with the same extension.
408	Indicates a time-out meaning that server took a long time respond.

VoIP interaction with cellular calls

A mobile device cannot have an active cellular call and an active VoIP call at the same time. Cellular calls have precedence over VoIP calls.

- When a cellular call is active or on hold, and you have an incoming VoIP call, the call continues to ring on any other phones that you have configured to ring simultaneously. If you do not receive the VoIP call on any of the configured devices, the call is displayed in the call history as a missed call.
- If you answer an incoming cellular call, while a VoIP call is active, the VoIP call is automatically put on hold. The only option available is to end the call. You can manually pick up the VoIP call that was on hold after you end the cell call.
- When a VoIP call is automatically put on hold because of a cell call, only the *End Call* VoIP in-call action is enabled. The others are disabled.
- If you are on an active mobility VoIP call during a transition from a cellular network to a Wi-Fi network or from a Wi-Fi network to a cellular network, the call is disconnected permanently. After the mobile device is connected to a new network, Avaya one-X® Mobile registers again with if the VoIP feature is configured for both the networks. You can start using Avaya one-X® Mobile for making and receiving fresh calls after the application is registered with .

Making VoIP Calls


To make VoIP calls, you must designate VoIP as the facility for placing outgoing calls. Use the Call Facility button on your Home screen to configure VoIP as the facility for placing your outgoing calls. You can make VoIP calls from any of these:

- Contact screen
- IM conversation window
- Dialpad
- Call Log
- Voicemail
- Geo-location map
- Join Conference


Receiving VoIP Calls

When your VoIP client is registered and active, and you have a call on your extension, the VoIP client displays an incoming call dialog box and the mobile device rings as per the sound settings in the device. However, you can configure the Ringtone using the application settings from *Menu>Settings>Voice Over IP>Ringtone*. If the mobile device is in sleep mode, it will be activated and the mobile device will ring. The incoming call dialog box can show multiple incoming calls if the call waiting feature is enabled for your mobile device from Manager.

The incoming call dialog box appears on the home screen of your mobile device when you receive a call:



After you tap the Answer button, the **Active Call** tab displays the active voice calls.



No.	Description
1	Indicates number of calls
2	Indicates a VoIP call

Interacting with VoIP Calls

When you make or receive a VoIP call, the Active Call tab displays the number of calls on your application. The application displays call information and provides you options to handle the calls when the call is on. The following screenshot provides you a view of the call area during an active VoIP call and the description and use of different components:



No.	Description
1	Indicates number of active calls.
2	Use to switch between active calls and the Dialpad. You can also swipe screen left or right to switch between active calls and the Dialpad.
3	Use to hold or unhold a call.
4	Use to mute or unumte a call.
5	Use to display the keypad to input DTMF tones.
6	Use to end a call.
7	Indicates current page.
8	Use to view call statistics.
9	Use to toggle between handset, speaker, and bluetooth.
10	Use to initiate a blind or consultative call transfer.
11	Indicates a VoIP call.
12	Displays far-end avatar, display name, state of the call, caller Id, and call duration.

Configuring Codec preferences

You can configure the Avaya one-X® Mobile application to use codecs appropriate for your network. Selecting an appropriate codec for your network enhances the quality of audio during a call. Avaya one-X® Mobile provides you with the option of selecting codecs depending on the network you are using. You can enable, disable, or change the order of the codecs for Wi-Fi network and Mobile network.

Procedure

1. Navigate to **Menu** > **Settings** > **Voice Over IP** > **Codec Preferences**.
2. Perform any one of the following actions:
   - To configure codecs to use while connected to Wi-Fi, tap **Wi-Fi codec list**.
   - To configure codecs to use while connected to mobile network, tap **Mobile network codec list**.

   Depending on your selection, either Wi-Fi codec list or Mobile network codec list appears on your screen.
3. You can perform any of the following actions on the codecs:
   - To disable a codec, tap the codec and ensure that the corresponding check box is cleared.
   - To move a codec up the list, long-press the codec and tap **Move up** on the Audio Codec Configuration screen.
   - To move a codec down the list, long-press the codec and tap **Move down** on the Audio Codec Configuration screen.

Enabling or disabling notification for VoIP registration

You can configure the Avaya one-X® Mobile application to notify you when your extension is registered to

About this task

Use the following procedure to enable or disable notification settings for VoIP registration.

Procedure

1. Navigate to **Menu** > **Settings** > **Notifications**.
2. Perform any one of the following actions:
   - To enable notifications, tap **VoIP Registration** and ensure that the corresponding check box is selected.
   - To disable notifications, tap **VoIP Registration** and ensure that the corresponding check box is cleared.

Configuring bluetooth headset support for VoIP calls

You can configure the Avaya one-X® Mobile application to automatically use bluetooth headsets for VoIP calls. However, Avaya one-X® Mobile in VoIP mode integrates with bluetooth headsets only at audio level. You can use bluetooth headsets only for speaking, listening, and controlling the audio volume during a VoIP call. Avaya one-X® Mobile does not support the following bluetooth features during a VoIP call:

- Use of keys to make or release a VoIP call.
- Display of information about incoming or active VoIP calls on car kit.
- Interaction with the application through voice commands.
- Access to Contacts in the application through bluetooth device.

About this task

Use the following procedure to configure bluetooth headset support for VoIP calls.

Procedure

1. Navigate to **Menu** > **Settings** > **Voice over IP**.
2. Tap **Auto connect Bluetooth** and ensure that the corresponding check box is selected.

Recording VoIP calls

About this task

Use this procedure to record a VoIP call. You can record only an ongoing call.

Important:

If you put an ongoing VoIP call on hold, the application disables the call recording feature for the call.

Procedure

1. During an ongoing call, tap **More**.

   The application displays the **Start Recording** icon.
2. Tap **Start Recording**.

   The application provides an audio confirmation that the call is being recorded.
3. Tap **Stop** or end the call to stop recording.

   The application sends the recorded call to the voice mail folder.

Chapter 8: Using instant messaging

Sending an instant message

Use the following procedure to send an instant message to a contact. You can send Instant Messages (IM) to multiple contacts using the **Select** icon.

Procedure

1. On the Contacts screen, to open a communication screen for a contact, tap the name of that contact.


   Note:

   If you sending an instant message to the Broadcast Group *everyone*, only users that can receive IMs can view your message. Basic users and external contacts, such as contacts using Google Talk and Google Mail, do not receive the message.

2. Tap **Send IM**.
3. Choose one of the following options:
   - Tap the microphone icon to compose your message using speech-to-text.
   - Tap the text field to open a keypad and type your text message.
   - Tap the emoticon icon to view and use emoticons.
4. After you enter your message, tap **Send**.

Receiving instant messages

The home screen displays a message when you receive a new instant message. If you have instant messages from more than one contact, a series of dots appear below the text to indicate how many messages are available for viewing. You can swipe to view the messages. To continue an instant message conversation, you must select the message.



If you experience issues receiving instant messages in the Avaya one-X® Mobile application, verify whether you have logged in to multiple XMPP clients at the same time. When you log into multiple XMPP clients, IMs are sent to where the presence indicates the best availability. For example, if you are logged in to the Avaya one-X® Mobile application and have a presence of “Away,” and you are also logged in to the Avaya one-X® Portal with a presence of “Available,” the instant message is sent to the Avaya one-X® Portal.

Configuring call out for incoming message

About this task

Use the following procedure to enable call out for an incoming message. If you enable the speak text feature, the application reads the incoming text message or the number of unread text messages. The speak text feature functions in the following cases:

- When your Android device is locked.
- When the Avaya one-X® Mobile application is in the minimized state.
- When you are in any other tab other than the IM conversation window of the contact you are chatting with.
- If you are offline and have received IMs. Only the count of the unread IMs is read out when you come online.

Procedure

1. On the Avaya one-X® Mobile application screen, navigate to **Menu** > **Settings**.
2. To enable call out for an incoming message, select the **Speak Messages** check box.

Selecting a view

By default, the Instant Message screen displays both read and unread instant messages. You can toggle between this view and a view that lists only unread instant messages.

Procedure

1. On the mobile phone, navigate to the Instant Message screen and press the menu key.
2. If you do not want to view the previously read IMs, tap **Disable History**.

Deleting instant messages

Use the following procedure to delete IMs that you have read. The Avaya one-X® Mobile application stores up to one megabyte of IMs. If you reach the storage limit, the application automatically deletes the oldest messages.

Procedure

1. On the mobile phone, navigate to the Instant Message screen and press the menu key.
2. To delete the previously read IMs, tap **Clear History**.
3. To confirm the deletion, tap **Yes**.

Sending text messages using voice commands

Before you begin

- Ensure that the Apple device supports Siri.
- Activate Siri.

About this task

In the IM screen, you can send text messages through voice commands using the speech-to-text feature

Procedure

1. On the Avaya one-X® Mobile applications screen, tap a contact to view a list of actions.
2. Tap the im icon .
3. On the keyboard, tap the microphone icon .
4. Speak the words, and tap **Done**.

   The application converts voice input to text and enters in the text field.
5. Tap **Send**.

Initiating a group chat

About this task

Use this task to initiate a group chat from the Contacts screen.

Note:

Only the moderator of the chat group can add contacts, delete contacts, or delete the chat group.

Only those applications that support the Group Chat functionality can participate in the group chat.

After all participants leave, the chat room ceases to exist.

Procedure

1. On the Contacts screen, long press the contacts you want to invite to the chat.

   The application displays the menu icon  at the top right corner.

2. Tap the menu icon and select **Create Group Chat**.
3. On the Create Group Chat dialog box, type a name for the chat room.

   The application does not support special characters such as “\”, “&”, “@”, and so on in the chat room name.

4. Tap **Create Group Chat**

   The chat room opens with the names of the contacts who have joined the chat room.

5. To add more contacts to the chat screen, tap the add contacts icon.
6. Select the contacts from the available contacts screen and tap **Invite Selected**.
7. To view information about the group, tap the group information icon.

   The application displays the following options:

   - **Created by**: Displays the name of the person who created the group.
   - **Remove Selected**: Tap this icon to remove participants from the group chat.
   - Option to delete the chat room.

Chapter 9: Managing voice mails

Managing voicemail

The Voicemail screen on the Avaya one-X® Mobile provides visual access to your voicemail messages. The voicemail screen supplies information about messages and provides controls that allow you to play messages and organize them.

The Voicemail screen also lets the user send voicemail messages to an e-mail address. For more information, see Sending voicemail messages through e-mail on page 73.

On Android devices, the SD card stores voicemail messages and, as such, the voicemail messages will not be available if you remove the SD card.

Voicemail messages are pre-downloaded and stored on the SD card, but only if the WiFi download mode is set to **Always**. With this setting, you are free to go offline and the pre-downloaded messages will still be available. They only become unavailable if they have not had a chance to download or if they have been deleted from the SD card. Likewise, when you select a message, the application searches the voicemail cache to avoid re-downloading.

Note that if you change user settings, such as the server configuration or the username and password, Avaya one-X® Mobile will drop all the downloaded messages and clear the voicemail list.

Note also that three seconds pass between downloads because downloaded messages require processing time to enter the cache.

Listening to voice mail messages

You can play, pause, fast forward, and rewind voice mail messages. The message opens and plays in the default player installed on your mobile phone.

Procedure

To open a voice mail message, tap the red **Play** button on the voice mail message.

The message begins to play automatically in the default player installed on your mobile phone.

Listening to incoming messages

Use the Avaya one-X® Mobile application to listen to an incoming voice mail while the message is in progress, or intercept and answer a call while a message is in progress.

Procedure

For an incoming voice mail message, click on any of the following options on the Home screen:

a. To listen to the incoming voice mail message as the message is being recorded, tap **Listen**.

b. To pick up the incoming voice mail message, tap **Answer**.

   If you answer an incoming voice mail message, the call rings at the location that you specify as your current location in the Avaya one-X® Mobile application.

Returning a call

If you receive a voice mail message, you can initiate a return call directly from the voice mail message.

About this task

Before you return a call, you can check the availability of the contact by checking the presence status of the contact on the voice mail message.

Procedure

1. On the Voicemail screen, locate the message for which you want to return a call.
2. To open the message, tap the message.
3. Check the presence status of the caller.
4. Press the voicemail message, and tap **Call**.

Deleting voice mail messages

Procedure

1. On the Voicemail screen, locate the message that you want to delete.
2. Tap the voice mail message.
3. Tap the delete icon 

Sending a voice mail message via email

You can send a voice mail message to the e-mail address of a contact using the following procedure.

Procedure

1. Press a voice mail message.
2. Tap **Send via Email**.
3. Select the method of e-mail and proceed accordingly.

Chapter 10: Managing geo-presence information

Avaya one-X® Mobile uses the on-board GPS in a mobile phone to provide information about the geographical location of a user, known as geo-presence. Use the geo-presence feature to view the geo-presence of your contacts if the contacts agree to share this information. Similarly, if you decide to share your geo-presence, Avaya one-X® Mobile can publish your geographic location to other users.

If you publish your geographic location to other Avaya one-X® Mobile users, the application provides real time information. However, if real time information is unavailable, Avaya one-X® Mobile uses information stored on the server to provide your last published location. For example, you are in a location where a satellite signal is unavailable.

To use this feature, you must enable GPS on your mobile phone, and enable geo-presence in Avaya one-X® Mobile. For information on enabling geo-presence, and setting the level of information to publish, see Configuring GPS information on page 32.

When you view the geo-presence of other contacts, you can view the location of your contacts on a map and see specific location information. You can also place a call to that contact, send an instant message, or add the contact to a conference directly from the map view.

When you publish your own geo-presence, you can see whether a contact has requested for your geo-presence information.

Viewing the geo-presence of a contact

Procedure

1. On the Contacts screen, check whether the contact is sharing the geo-presence information.

   If the geo-presence information is available, the application displays a place marker icon next to the name of the contact.

2. To open a communication screen for that contact, tap the name of the contact.
3. Tap **Details**.

   If the geo-presence information is available for that contact, the application displays the information in the **Location Information** area.

4. To view the location on a map, tap the location name.

Viewing requests for your geo-presence

Use the following procedure to see whether a contact has requested your geo-presence information.

Procedure

1. On the Contacts screen, to open a communication screen for a contact, tap the name of that contact.
2. Tap **Details**.

   A dialog box indicates whether the contact has requested your geo-presence information.

Next steps

For information about setting the level of information to publish, see Configuring GPS information on page 32.

Communications options

In addition to viewing the current location of a contact on a map, you can place a call to that contact, send an instant message, or add the contact to a conference directly from the map view.

Procedure

From the map view, press the placemarker to open a menu and select one of the following options:

- Unpin from map
- Call
- Add to conference
- Send IM
- Show location information

Chapter 11: Sharing the application feedback

You can share the application feedback through Facebook, Twitter, Mail, and through Message.

Sharing feedback through Facebook

Before you begin

Configure Facebook on your Android device.

Procedure

1. On the Avaya one-X® Mobile application screen, navigate to **Menu** > **Settings**.
2. On the Settings screen, tap **Share**.
3. On the Share screen, tap **Facebook**.

   Your Android device displays the Share screen of Facebook with a description of Avaya one-X® Mobile Preferred for IP Office application.
4. In the Say something about this.. text box, type a feedback message.
5. Tap **Share**.

Sharing feedback through Twitter

Before you begin

Configure Twitter on your Android device.

Procedure

1. On the Avaya one-X® Mobile application screen, navigate to **Menu** > **Settings**.
2. On the Settings screen, tap **Share**.
3. On theShare screen, tap **Twitter**.

   The application displays a Twitter dialog box.

4. **(Optional)** On the Twitter dialog box, you can perform the following actions:
    a. In the message text box, either edit the default feedback message or type a new feedback message.
    b. If you want to show your location details, tap the location icon.
    c. Enter the location in the Search locations search box. If you do not want to select any location, tap the delete icon .
    d. If you want to attach an image, tap the camera icon.

       The application displays the Select media screen.
    e. Select one or more images and tap **Done**.
5. Tap **Tweet**.

Sharing feedback through Mail

Before you begin

Configure the device Mail.

Procedure

1. On the Avaya one-X® Mobile application screen, navigate to **Menu** > **Settings**.
2. On the Settings screen, tap **Share**.
3. On the Share screen, tap **Mail**.

   If you have more than one email client installed on your Android device, the application displays a Send to dialog box.
4. Select the email client through which you want to share the feedback.

   The application opens an Email with a default subject and a default feedback content. You can edit either the subject or content or both.
5. In the **To** and **Cc/Bcc** field select or type the email address of the intended recipient.
6. Tap the send icon.

Sharing feedback through Message

Procedure

1. On the Avaya one-X® Mobile application screen, navigate to **Menu** > **Settings**.
2. On the Settings screen, tap **Share**.
3. On the Share screen, tap **Message**.

The application opens a new message with default feedback content. You can edit the content.

4. In the **To** field, select the name of the intended recipient. You can also type the name or number of the intended recipient.
5. Tap **Send**.

Chapter 12: Troubleshooting

Uploading logs

Avaya one-X® Mobile collects logs continuously. You can upload these logs to the one-X server using the following procedure.

Procedure

1. On your mobile device, tap **Menu**.
2. Tap **Log Upload**.

Submitting a problem

If you come across any problem while using Avaya one-X® Mobile, you can report the problem using the following procedure:

Procedure

1. On your mobile device, select **Menu** > **Settings** > **Advanced**.
2. Tap **Submit Problem Report**.
3. Enter the description of the problem.
4. Tap **Submit**.

Index

Numerics

3PCC 27
3rd-party call control 27
3rd-party calls 47

A

adhoc conference 55
avatar 9

B

bluetooth headset support 65, 66

C

calendar
    enable publishing 37
    viewing 41
call 66
call any number 47
call control 27
call facility 42
calling
    from voicemail 72
Call Log 45
call move 48
call out
    instant message 68
call record 66
call status
    enable publishing 37
call transfer 47, 48
change password
    password change 36
clearing
    event history 58
codec preferences 65
conference
    join 54
    start 52
conference bridge
    configuring 37
conference calls: about 50
conference calls: adding participants 51
conference calls: disconnecting 55
conference calls: locking 54
conference calls: muting participants 54
configuration
    bluetooth headset support 65, 66
    codec preferences 65
    do not disturb 35
    enterprise dialing 29
    geo-presence 32
    notifications 31
    widget 36
configuration: connection to IP Office 26
configuring
    notification settings for missed calls 58
    quality improvement 35

D

dial plan
    enterprise dialing 29
dnd 35
do not disturb 35
duplicate 38

E

email 73
e-mail 44, 46
enabling or disabling 33
enterprise dialing 29
event history
    clearing 58
events history
    filtering 58
Events history 57

F

feature
    Events history 57
    VoIP 59
feedback 76
filtering
    events history 58

G

geo-presence 32
    deleting 32
GPS information 32
    deleting 32
group chat
    initiate 69

I

IM 67
installation 25

installation *(continued)*
Android devices 25
instant message
call out 68
click-to-call 45
instant messages 67
instant messages: sending 67
interacting with VoIP calls 63
interface
Call Log 22
Conference screen 20
Home screen 13
Instant Message screen 18
interface: Android: about 9
interface: Android: Contacts screen 14
interface: Android: layout 9
interface: Android: menu key 13
interface: Android: navigation bar 11
interface: Android: status bar 10
interface: icons 12
IP Office: configuring the connection 26

J

join
conference 54

M

mail 76
making
selection 46
making VoIP calls 62
Menu Guide
screen 14
merging calls 55
message 76, 77
missed call notification
configuring 58
mobile twinning 33
move call 48
moving a call 48

N

notifications 31
Notify Me feature
configuring 30
numbers on native applications 47

P

password 36
phone status
viewing 41
presence
following contacts 40
monitoring contacts 40
setting 40

R

read out name for incoming call 47
receiving VoIP calls 62
record call 66
recording 66

S

screen
Menu Guide 14
setting
speak caller name 47
share 76, 77
sharing 76
sharing feedback
through facebook 76
through Mail 77
through Twitter 76
speech to text 69
start
conference 52
starting
adhoc conference 55
status
contacts 40
setting presence 40
status: user presence 38
submitting a problem 79

T

text message 69
twitter 76

U

upload logs 79
user call monitoring 28, 48
user call transfers 48

V

viewing
emergency calls disclaimer 36
voice mail 73
deleting 72
intercept incoming 72
listening to messages in progress 72
playing messages 71
returning a call 72
Voice over IP 27

VoIP 27
error messages 61
prerequisites 59
status indicators 60
supported devices 59
VoIP calls 62, 63
VoIP feature 59
VoIP interaction
cellular calls 61